

- Auto ranging hand held 3½ digit Digital Multimeter with large LCD display incorporating latest technology
- This Digital Multimeter can measure AC Voltage, DC Voltage, AC Current, DC Current, Resistance, Temperature
- Additional Features include Diode Test, Transistor check, Continuity check, Low Battery display, Data Hold Maximum Hold, Battery check and Auto Power Off
- This Digital Multimeter has a built-in holster for anti sliding



Model No:- 16972

FUNCTIONS	RANGE	BASIC ACCURACY
Voltage DC	200mV/2V/20V/200V/1000V	± (0.5%+3dgts)
Voltage AC	200mV/2V/20V/200V/1000V	± (1.2%+3dgts)
Ampere DC	200µA/2000µA/20mA/200mA/2A/10A	± (0.8%+3dgts)
Ampere AC	200µA/2000µA/20mA/200mA/2A/10A	± (1.0%+3dgts)
Ampere AC (with clamp CT 600*)	200A (Resolution : 1mV / 1A)	± (1.5%+5dgts)
	600A (Resolution : 1mV / 10A)	
Resistance	200Ω/2KΩ/20KΩ/200KΩ/2M /20M	± (1.5%+3dgts)
Temperature	-40°C ~ 1370°C/ -40°F ~ 2000°F	± (1.0%+4dgts)
SPECIAL FUNCTIONS		
Transistor Test		✓
Diode Testing		✓
Continuity Test		✓
On off warning		✓
Battery Test	1.5V/3.0V/9.0V	✓
Low Battery display		✓
Maximum Hold		
Data hold		✓
Auto Power off		✓
Operating Mode	Auto ranging / Manual range	✓
Maximum Display	1999	
Display Size	63mmX32mm	
Power Supply	AAA 1.5V (2 batteries)	

Clamps CT 600: optional (at extra cost)

Accessories with the Meter



K-Type Thermocouple Lead



Test Leads



Multifunction Socket

Note: Specifications are subject to change.

Tesca Technologies Pvt. Ltd.

IT-2013, Ramchandrapura Industrial Area, Sitapura Extension,
Near Bombay Hospital, Vidhani Circle, Jaipur-302022, Rajasthan, India,
Tel: +91-141-2771791 / 2771792; Email: info@tesca.in, tesca.technologies@gmail.com
Website: www.tesca.in

